

.....[®]
CALRAD
ELECTRONICS

819 N. Highland Ave.
 Los Angeles, CA 90038

Tel (323) 465-2131, Fax (323) 465-3504
 Visit us on the web at www.calrad.com

New

Part No. 15-133
4 Channel Stereo
Headphone Amplifier



Calrads new headphone distribution amplifier allows low or line-level sources to drive up to 6 pairs of stereo headphones. 6 separate amplifiers drive any mix of headphones from 8 to 600 ohms and each headphone has its own stereo volume control. The rugged steel metal case with rubber end caps makes this unit durable for any environment.



Adapter Included

1



Headphones 1

2



Headphones 2

3



Headphones 3

4



Headphones 4

Specifications:

Input Impedance: 100K Ohms unbalanced
 Output Impedance drives 8 Ohms, 32 Ohms, 600 Ohms
 Max Input Level: +14 dBV Input
 Input/Output Connectors: (5) Stereo 1/4 in. TRS phone jacks.
 Max Gain: 20 dB/Channel
 S/N Ratio: >90 dB
 THD: <.008 IMD (SMPTE) <.008
 DC Power: 12Vdc, 300ma
 Weight: 1 lb (.45 kg)

Optional Accessories:

35-550

Stereo 1/4" Male Plug
 to 1/8" Female Jack



55-899-6S

Stereo 1/4" Male Plug
 to RCA Male Jacks, 6 ft.

