

819 N. Highland Ave. Los Angeles, CA 90038 Tel (323) 465-2131, Fax (323) 465-3504

40-SDI-1 HD-SDI TO HDMI CONVERTER WITH LOOP OUT

Convert 3G/HD/SDI to HDMI, 2 Channel stereo audio. Built in Equalizer to increase the working distance and signal reliability. SDI Loop Out with Retiming function to have the best output quality.



- SDI Standard / Protocol:
 SDI (SMTP 259M), HD-SDI (SMTP 292M), 3G-SDI (SMTP 424M)
- Video Support: NTSC (480i), PAL (576i),
 720p@50/59.94/60Hz,
 1080p@23.98/24/29.97/30/50/59.94/60Hz
- SDI Input Connector: BNC 75 Ω , SDI Output Connector: BNC 75 Ω
- Audio Support: 2 channel Stereo Audio
- Built in Equalizer to increase the working distance and signal reliability.
- SDI Loop Out with Retiming function to have the best output quality.
- \bullet Temperaturep Oeration: 0 to 55 Celcius, Storage: -20 to 85 Celcius, Humidity: up to 95%
- Power Consumption: 750mA (Max)
- Power Supply: Switching DC5V 1AMP
- Dimensions:
 67mm (L) x 110mm (W) x 27mm (H)
- Weight: 185 g






Example Diagram:

HD Camera

HD-SDI Camera





SDI Monitor



SDI DVR



40-SDI-1